



# DASIG X2

## WIRELESS GAMING MOUSE

<https://rakk.ph/>

### 1.0 Specifications:

Sensor	Pixart PMW3325
MCU	Telink 8271
Connectivity	Triple Mode (wired, 2.4g, BT 5.1 )
Battery	600mA Battery
No. of buttons	8
Switches / Clickers	Huano 80M for L/R buttons   Huano 3M for side
Size/Dimension	125 x 63.5 x 40.5mm
Weight	80g ± 3g
DPI	Up to 10000 DPI
IPS	100
Acceleration	20g
Polling Rate	up to 1000 Hz   125 hz for BT
Cable	1.6m paracord
Charging Time	3~4hours
Software	Yes Download at rakk.ph
Accessories	Paracord Type-C cable
System	Android, Windows and MAC

### 2.0 Connectivity:

- Wired Mode - Plug in Type-C cable USB plug and play

- 2.4G Wireless Mode - Unplug the cable, toggle up the power switch to the 2.4G wireless mode and insert the USB dongle

Pairing (if needed): Pressing the left, middle, right button together for 3 seconds, plug in the receiver while the indicator light flash, if the lights turn on green , means the match is successful

- BT 5.1 Mode - Unplug the cable, toggle down the power switch to enter the BT 5.1 mode. Press the left, middle, right button for 3 seconds, when the blue light flash rapidly, open Bluetooth on the computer and search for Bluetooth name: RAKK DASIG X2, blue light stop flashing means that Bluetooth connection is successful.

### 3.0 Battery:

- Red light flashes - Low Battery and Charging
- Green light (steady) - Fully Charged
- Sleeping mode - 30 minutes

### 4.0 Material:

MATERIAL	SPECIFICATION
Up Cover	ABS
Bottom	ABS
Skates	PTFE

<https://rakk.ph/>